

XGZP6182 EVAPORATIVE FUEL PRESSURE SENSOR

Datasheet

Version: V1.0

Approved Date: 2022.05.13



Index

| 1.FEATURES | 4 |
|----------------------------|---|
| 2.APPLICATIONS | 4 |
| 3.DESCRIPTIONS | |
| 4.PERFORMANCE PARAMETER | 4 |
| 5.ELECTRICAL SPECIFICATION | 5 |
| 6.DIMENSION (Unit: mm) | 6 |
| 7.ELECTRICAL CONNECTION | 6 |
| 8.OUTPUR CURVE | 6 |
| 9.ORDER GUIDE: | 7 |
| 10.NOTICE&ATTENTION | 7 |



Revision History


| Revision | Description | Date |
|----------|-------------|------------|
| V1.0 | Original | 2022.05.13 |
| | | |
| | | |
| | | |
| | | |

The information in this sheet has been carefully reviewed and is believed to be accurate; however, no responsibility is assumed for inaccuracies. Furthermore, this information does not convey to the purchaser of such devices any license under the patent rights to the manufacturer. CFSensor reserves the right to make changes without further notice to any product herein. CFSensor makes no warranty, representation or guarantee regarding the suitability of its product for any particular purpose, nor does CFSensor assume any liability arising out of the application or use of any product or circuit and specifically disclaims any and all liability, including without limitation consequential or incidental damages. Typical parameters can and do vary in different applications. All operating parameters must be validated for each customer application by customer's technical experts. CFSensor does not convey any license under its patent rights nor the rights of others.



1.FEATURE

This product is made with advanced MEMS principles, and the core technology is piezoresistive based MEMS pressure sensor chip and high performance signal conditioning AISC chip is of high quality and precise packaging.



Using experienced and reliable technology on calibration, compensation and protection, Fast response speed, high reliability, good stability, it's a cost-effective sensor product. The evaporative fuel pressure sensor is a real-time pressure measurement in the fuel tube, which ensures that the carbon canister system works properly and reduces emissions.

2.APPLICATION

Applied in automobile fuel tank, for monitoring the pressure difference between the pressure of the vehicle fuel tank and the ambient air pressure, and convert the pressure difference signal into an analog voltage signal, which is transferred to the ECU/ECM of the automobile to realize the diagnosis of oil and gas leakage in the fuel tank.

3.DESCRIPTION

XGZP6182 is a calibrated fuel evaporative fuel pressure sensor product launched by CFSensor for the automotive market. This product uses an automotive-grade signal conditioning chip to calibrate and compensate the output of the MEMS chip, and can adjust from -3.75kPa to +1.25kPa is converted into an analog output signal of 4.5V to 0.5V (range and output can be customized).

4.PERFORMACE PARAMETER

Power supply: (5 ± 0.25) V DC

Refered Temperature: 25°C

Figure 1. Performance Parameter




| Subject | Value | Unit |
|-----------------------------|---|--------|
| Range | -3.75 ~ +1.25 (customized) | kPa |
| Output | 4.5 ~ 0.5 (customized with ratio output or fixed output) | V |
| Accuracy | ±1.5 | %Span |
| Accuracy in Full Temp.Range | ±3 | %Span |
| Overload Pressure | 68 | KPa(G) |
| Burst Pressure | 300 | KPa(G) |
| Protection Grade | IP67 | |
| Response Time | €2 | mS |
| Clamp Vol.(up&down) | Customized as request. | |
| Insulance | ≥10MΩ/500VDC | ΜΩ |
| Working Temp. | -40 ~ 115 | ℃ |
| Store Temp. | -40 ~ 130 | ℃ |

5.ELECTRICAL SPECIFICATION

Figure 2. Electrical Specification

| Parameter | Min. | Тур. | Max. | Unit | Remark |
|----------------------------------|------|------|------|------|--------|
| Power Supply | 4.75 | 5 | 5.25 | V | |
| Working Current | | | 10 | mA | |
| Overload Voltage | | | 18 | V | |
| Reverse Voltage | | | -14 | V | |
| Output Load | | | 5 | mA | |
| Short-circuit Current Limitation | 15 | 20 | 25 | mA | |
| Output Load(pull down) | | 47 | | ΚΩ | |
| Output Load(pull up) | | 100 | | ΚΩ | |

6.DIMENSION (UNIT: mm)



7. ELCTRICAL CONNECTION

The recommended model of the female terminal of the electrical connector: DELPHI PACKARD PART NO. 12059595




Image 1. PIN Schema

Figure 3. PIN Definition

| No. | Description | Remark |
|-----|-------------|----------------------------------|
| 1 | VCC | Power supply Postive (5±0.25VDC) |
| 2 | Vout | Output(Voltage signal) |
| 3 | GND | Power supply Negative |



8. OUTPUT CURVE

Curve Formula: Vout/Vcc = 0.3-0.16* P

Remark:

Vcc: Power supply Unit: V;

P: Pressure value (Difference value between fuel tube and atmosphere pressure) ,Unit: kPa;

Vout: Output Voltage Unit: V




Image 2 Output VS Pressure Curve

9.ORDER GUIDE:

Contact CFSesnor if you have special requirements on the performance parameters and functions of the product,

10.NOTICE&ATTENTION

- 1) The sensor can only be unpacked before being installed on the engine
- 2) The sensor is designed to measure the fuel tank pressure of the internal-combustion engine using gasoline, diesel, LNG or CNG as fuel, and is not allowed to be used in other occasions;
- 3) The normal packaged pressure sensor can be transported by ordinary conveying means. Please Note: Product is protected from moisture, shock, sunburn and stress during shipping.
- 4) If you have any questions, please contact CFSensor
- Since this specification is a single product specification, in order to improve the reliability in actual use, please confirm the performance and quality in the actual use state.



SAFETY NOTES

Using these sensors products may malfunction due to external interference and surges, therefore, please confirm the performance and quality in actual use. Just in case, please make a safety design on the device (fuse, circuit breaker, such as the installation of protection circuits, multiple devices, etc.), so it would not harm life, body, property, etc even a malfunction occurs. To prevent injuries and accidents, please be sure to observe the following items:

- The driving current and voltage should be used below the rated value.
- Please follow the terminal connection diagram for wiring. Especially for the reverse connection of the power supply, it will cause an accident due to circuit damage such as heat, smoke, fire, etc.
- In order to ensure safety, especially for important uses, please be sure to consider double safety circuit configuration.
- Do not apply pressure above the maximum applied pressure. In addition, please be careful not to mix foreign matter into the pressure medium. Otherwise, the sensor will be discarded, or the media will blew out and cause an accident.
- Be careful when fixing the product and connecting the pressure inlet. Otherwise, accidents may occur due to sensor scattering and the blowing out of the media.